

Accepted Manuscript

Error Theory of Chord-based Measurement System regarding Track Geometry and Improvement by High Frequency Sampling

Ping Wang, Yuan Wang, Huiyue Tang, Mingyuan Gao, Rong Chen, Jingmang Xu

PII: S0263-2241(17)30643-7

DOI: <https://doi.org/10.1016/j.measurement.2017.10.019>

Reference: MEASUR 5021

To appear in: *Measurement*

Received Date: 29 April 2016

Revised Date: 15 June 2017

Accepted Date: 11 October 2017

Please cite this article as: P. Wang, Y. Wang, H. Tang, M. Gao, R. Chen, J. Xu, Error Theory of Chord-based Measurement System regarding Track Geometry and Improvement by High Frequency Sampling, *Measurement* (2017), doi: <https://doi.org/10.1016/j.measurement.2017.10.019>

This is a PDF file of an unedited manuscript that has been accepted for publication. As a service to our customers we are providing this early version of the manuscript. The manuscript will undergo copyediting, typesetting, and review of the resulting proof before it is published in its final form. Please note that during the production process errors may be discovered which could affect the content, and all legal disclaimers that apply to the journal pertain.



Error Theory of Chord-based Measurement System regarding Track Geometry and Improvement by High Frequency Sampling

Ping Wang^{a,c}, Yuan Wang^{a,c}, Huiyue Tang^{b,c}, Mingyuan Gao^{a,c}, Rong Chen^{a,c,*}, Jingmang Xu^{a,c}

^a Key Laboratory of the Ministry of Education, High speed railway engineering

^b Train control and traction drive laboratory

^c Southwest Jiaotong University, No. 111, North 1st Section of Second Ring Road, Chengdu City, Sichuan, PRC, 610031

* Correspondence should be addressed to Rong Chen: chenrong@home.swjtu.edu.cn

Abstract: The chord-based measurement system has been used for a long time in the measurement of track irregularity, however, the error theory is seldom studied. As a typical case, the mid-chord offset system (MCO-system) is selected in this paper to study the error propagation of chord-based systems. The measurement model and restoration model are established to describe the measurement and restoration process of the MCO-system. To evaluate the accumulation of error, the Error Amplification Factor (EAF) is defined. The regularities of error accumulation are analyzed in the distance domain and the wavelength domain. Furthermore, an error propagation formula of different wavelengths is proposed. High frequency sampling is introduced to improve the performance of the MCO-system, where a least square model is established to handle the redundant measured data, and it can be theoretically proven that the influence of measuring errors can be reduced to zero if the sampling frequency approaches infinity. The error theory given in this paper is useful for designing devices based on the MCO-system and the error of different wavelengths can be accurately controlled. As an application, field measurement is carried out to verify the feasibility and correctness of the models by comparison with the restoration method using a digital inverse filter.

Keywords: Chord-based measurement; Track geometry irregularity; Error amplification factor; Error analysis; High frequency sampling

1 Introduction

Efficient and fast detection of track geometry irregularities is of crucial importance to high-speed railway maintenance. It is not only related to the vibration and noise of the environment, but also affects the traveling safety and comfort of the running vehicles [1-6]. A variety of measurement principles have been developed regarding track geometry irregularities [1, 7-26]. Among them, chord-based measurement systems and inertial-based measurement systems are the dominant techniques.

In the case of chord-based measurement system, a reference chord is formed between two points on the rails and the distance between this reference chord and a third position of the rail is measured [1-2, 8]. This reference chord, generally with a length of about 1m, moves along the rail propelled by a trolley or vehicle to achieve a continuous measurement of rail geometry. During the chord measurement process, the data is always changing along the rail, leading to an amplitude variation (ranging from 0~2) of amplitude transfer function [1-2, 8-10]. For the mid-chord offset system (MCO-system), the wavelengths where the amplitude of transfer function equals zero, namely the zero points, repeat periodically; it is therefore impossible for those wavelengths to be measured. The amplitude behavior can be enhanced if the chord is asymmetric, but in this case the phase is distorted [1-2, 8]. Instead, inertial-based measurement systems are used due to the existence of an inertial reference frame of accelerometers: the data does not change during the measurement [1-2, 12-17]. The displacement is then determined by double integration of the

متن کامل مقاله

دریافت فوری ←

ISIArticles

مرجع مقالات تخصصی ایران

- ✓ امکان دانلود نسخه تمام متن مقالات انگلیسی
- ✓ امکان دانلود نسخه ترجمه شده مقالات
- ✓ پذیرش سفارش ترجمه تخصصی
- ✓ امکان جستجو در آرشیو جامعی از صدها موضوع و هزاران مقاله
- ✓ امکان دانلود رایگان ۲ صفحه اول هر مقاله
- ✓ امکان پرداخت اینترنتی با کلیه کارت های عضو شتاب
- ✓ دانلود فوری مقاله پس از پرداخت آنلاین
- ✓ پشتیبانی کامل خرید با بهره مندی از سیستم هوشمند رهگیری سفارشات